



TECHNICAL Practice

TELECOM SOLUTIONS FOR THE 21ST CENTURY

C-2000A

**Advanced Door/Gate
Entry Phone Controller**

June 9, 2006

Add 1-4 Entry Phones and Doorstrike Control to an Existing Phone Line

The **C-2000A** allows single line phones or phone systems to share a phone line with 1-4 entry phones. Tenants may answer an entry phone call, converse with the visitor and activate a contact closure to control electronic gates or door strikes.

The **C-2000A** provides "Caller ID" and will also provide "Call Waiting Caller ID" and a "Call Waiting" tone when the phone line is in use. Tenants may gain entry at each gate by entering a Touch Tone keyless entry code.

Tenants may call out to each entry phone for monitoring purposes. An auxiliary input is also available for connecting a lighted doorbell switch, a common garage door opener/receiver or an auxiliary keyless entry keypad.



Features

- Allows 1-4 entry phones to share a single telephone line with a residential or business telephone system
- Compatible with the following Viking entry phones:
 - **E-10, E-20A, E-30** and **E-40** Handsfree Phones
 - **K-1500-7** Stainless Steel Panel Phone
 - **K-1700-3** Handsfree Phone with Keypad
 - **K-1900-8** Stainless Steel Phone with Keypad
 - Or use with any analog touch tone phone
- **Provide entry phone activated chimes and whole house paging when used with Viking model SLP-1**
- **Up to 6 different keyless entry codes / "one time use" keyless entry codes per entrance**
- **Up to 6 master keyless entry codes for use at any entrance**
- Optional "Privacy Number" allows only selected visitors to call from an entry phone
- Provides "Caller ID" and "Call Waiting Caller ID"
- Produces "Call Waiting" tones
- **Lighted doorbell switch input to activate entry phone call**
- One set of normally open and normally closed contacts available for each entry phone (a second set is available on solder pads)
- Programmable contact activation time
- Auxiliary input to activate timed auxiliary contacts
- Realistic call progress tones

Applications

- Add one to four entry phones to your standard home or office phones to provide:
 - Door communication
 - Door entry
 - Gate entry
 - Keyless entry
- Provide commercial or residential security via two-way handsfree communication at the door and gate
- Connects in series with a single phone line or to a phone system's unused line input (loop start trunk input)

Phone...715.386.8861

<http://www.vikingelectronics.com>

Specifications

Power: 120VAC / 13.8VAC 1.25A, UL listed adapter provided
Dimensions: 210mm x 159mm x 45mm (8.25" x 6.25" x 1.75")
Shipping weight: 1.5kg (3.2 lbs.)
Environmental: 0°C to 32°C (32°F to 90°F) with 5% to 95% non-condensing humidity
Relay Contacts: 5A @ 30VDC/250VAC
Ring Output: 8 REN, capable of ringing (16) 0.5 REN phones
Talk Battery: 40V DC
REN: 0.1A
Connections: (30) cage clamp screw terminals

IF YOU HAVE A PROBLEM WITH A VIKING PRODUCT, PLEASE CONTACT: VIKING TECHNICAL SUPPORT AT (715) 386-8666

Our Technical Support Department is available for assistance Monday 8am - 4pm and Tuesday through Friday 8am - 5pm central time. So that we can give you better service, before you call please:

1. Know the model number, the serial number and what software version you have (see serial label).
2. Have your Technical Practice in front of you.
3. It is best if you are on site.

RETURNING PRODUCT FOR REPAIR

The following procedure is for equipment that needs repair:

1. Customer must contact Viking's Technical Support Department at 715-386-8666 to obtain a Return Authorization (RA) number. The customer MUST have a complete description of the problem, with all pertinent information regarding the defect, such as options set, conditions, symptoms, methods to duplicate problem, frequency of failure, etc.
2. Packing: Return equipment in original box or in proper packing so that damage will not occur while in transit. Static sensitive equipment such as a circuit board should be in an anti-static bag, sandwiched between foam and individually boxed. All equipment should be wrapped to avoid packing material lodging in or sticking to the equipment. Include ALL parts of the equipment. C.O.D. or freight collect shipments cannot be accepted. Ship cartons prepaid to: **Viking Electronics, 1531 Industrial St, Hudson, WI 54016**
3. Return shipping address: Be sure to include your return shipping address inside the box. We cannot ship to a PO Box.
4. RA number on carton: In large printing, write the R.A. number on the outside of each carton being returned.

RETURNING PRODUCT FOR EXCHANGE

The following procedure is for equipment that has failed out-of-box (within 10 days of purchase):

1. Customer must contact Viking's Technical Support at 715-386-8666 to determine possible causes for the problem. The customer MUST be able to step through recommended tests for diagnosis.
2. If the Technical Support Product Specialist determines that the equipment is defective based on the customer's input and troubleshooting, a Return Authorization (R.A.) number will be issued. This number is valid for fourteen (14) calendar days from the date of issue.
3. After obtaining the R.A. number, return the approved equipment to your distributor, referencing the R.A. number. Your distributor will then replace the product over the counter at no charge. The distributor will then return the product to Viking using the same R.A. number.
4. **The distributor will NOT exchange this product without first obtaining the R.A. number from you. If you haven't followed the steps listed in 1, 2 and 3, be aware that you will have to pay a restocking charge.**

WARRANTY

Viking warrants its products to be free from defects in the workmanship or materials, under normal use and service, for a period of one year from the date of purchase from any authorized Viking distributor or 18 months from the date manufactured, whichever ever is greater. If at any time during the warranty period, the product is deemed defective or malfunctions, return the product to Viking Electronics, Inc., 1531 Industrial Street, Hudson, WI, 54016. Customer must contact Viking's Technical Support Department at 715-386-8666 to obtain a Return Authorization (R.A.) number.

This warranty does not cover any damage to the product due to lightning, over voltage, under voltage, accident, misuse, abuse, negligence or any damage caused by use of the product by the purchaser or others. Viking's sole responsibility shall be to repair or replace (at Viking's option) the material within the terms stated above. VIKING SHALL NOT BE LIABLE FOR ANY LOSS OR DAMAGE OF ANY KIND INCLUDING INCIDENTAL OR CONSEQUENTIAL DAMAGES RESULTING DIRECTLY OR INDIRECTLY FROM ANY BREACH OF ANY WARRANTY EXPRESSED OR IMPLIED, OR FOR ANY OTHER FAILURE OF THIS PRODUCT. Some states do not allow the exclusion or limitation of incidental or consequential damages, so this limitation may not apply to you.

THIS WARRANTY IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THE WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY EXCLUDED BEYOND THE ONE YEAR DURATION OF THIS WARRANTY. Some states do not allow limitation on how long an implied warranty lasts, so the above limitation may not apply to you.

FCC REQUIREMENTS

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the ACTA. On the side of this equipment is a label that contains, among other information, a product identifier in the format US:AAAEQ#TXXXX. If requested, this number must be provided to the telephone company.

The REN is used to determine the number of devices that may be connected to a telephone line. Excessive REN's on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of the REN's should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total REN's, contact the local telephone company. For products approved after July 23, 2001, the REN for this product is part of the product identifier that has the format US:AAAEQ#TXXXX. The digits represented by # are the REN without a decimal point (e.g., 03 is a REN of 0.3). For earlier products, the REN is separately shown on the label.

The plug used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. If your home has specially wired alarm equipment connected to the telephone line, ensure the installation of this C-2000A does not disable your alarm equipment. If you have questions about what will disable alarm equipment, consult your telephone company or a qualified installer.

If the C-2000A causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice isn't practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations, or procedures that could affect the operation of the equipment. If this happens, the telephone company will provide advance notice in order for you to make the necessary modifications to maintain uninterrupted service.

If trouble is experienced with the C-2000A, for repair or warranty information, please contact:

Viking Electronics, Inc., 1531 Industrial Street, Hudson, WI 54016 (715) 386-8666

If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

Connection to Party Line Service is subject to State Tariffs. Contact the state public utility commission, public service commission or corporation commission for information.

WHEN PROGRAMMING EMERGENCY NUMBERS AND (OR) MAKING TEST CALLS TO EMERGENCY NUMBERS:


Remain on the line and briefly explain to the dispatcher the reason for the call. Perform such activities in the off-peak hours, such as early morning or late evenings.

It is recommended that the customer install an AC surge arrester in the AC outlet to which this device is connected. This is to avoid damaging the equipment caused by local lightning strikes and other electrical surges.

PART 15 LIMITATIONS

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Features Overview




Installation and Applications



IMPORTANT: Electronic devices are susceptible to lightning and power station electrical surges from both the AC outlet and the telephone line. It is recommended that a surge protector be installed to protect against such surges. Contact Panamax at (800) 472-5555 or Electronic Specialists Inc. at (800) 225-4876.


A. One to Four Entry Phones Sharing a Single Phone Line with House Phones

* **Note:** To increase surge protection, fasten a wire from the screw terminal to Earth Ground (grounding rod, water pipe, etc.)



B. Provide Whole House Paging with Unique Front and Back Door Chimes and Control Up to Four Entry Phones and Doorstrikes from a Single Phone Line

Note: To provide unique front and back door chimes, the C-2000A must have the "Auxiliary Contact Mode" enabled (DIP switch 1 OFF) and have the auxiliary contact programmed for "Entry Phone Triggered Ring Cadence Activation" (3#60). Entry phone ringing can also be disabled (0#62). If CCTV video control is required, up to (2) VC-1000's can be used. See Programming section B.




Need More Information on SLP-1? Call (715) 386-4345 and select 478.

C. Using a C-2000A without a C.O. Line


The **C-2000A** can also be used without a C.O. line. This is ideal for connecting the **C-2000A** to an unused trunk/line input of your phone system or connecting to phones used only for doorbox communication.

Step 1.	Connect the power, required entry phones and doorstrike outputs (if required) as shown in section A.
Step 2.	Connect an analog phone or unused phone system (PABX/KSU) line/trunk port to terminals 4 & 5, "LINE OUT TO PHONES" on the C-2000A .
Step 3.	Access programming as shown in Programming section A, 2. below. Enter *5, two beeps should be heard.
Step 4.	Enter additional desired programming, then hang-up the phone and place DIP switch 2 back to the OFF position.



D. Using the C-2000A with a Proximity Card Reader or a Separate Keyless Entry Keypad

Step 1.	Program the ES-1 "Relay Activation Time" to match the "Doorstrike Activation Time" on the C-2000A .
Step 2.	Connect the ES-1 relay output in parallel with the doorstrike output contacts on the C-2000A .
Step 3.	Connect the entry phones and doorstrike outputs (if required) as shown in section A.



Programming

A. Accessing Programming

1. Accessing the Programming Mode with a Security Code

Step 1.	Come off-hook with any house phone (device) connected to terminals 4 & 5, LINE OUT TO PHONES .
Step 2.	Enter *# followed by the 6-digit security code (factory set to 845464 , V-I-K-I-N-G, see Programming section C).
Step 3.	A double beep will indicate that you have accessed the programming mode.
Step 4.	You can now Touch Tone program the features listed in section B below.
Step 5.	When finished programming, hang up.

2. Accessing the Programming Mode Locally (Security Code Bypass Mode)

Note: This mode is useful for programming the **C-2000A** without a telephone line connected.

Step 1.	Move DIP switch 2 from OFF to ON (Security Code Bypass Mode, see DIP Switch Programming section D).
Step 2.	Come off-hook with any house phone connected to terminals 4 & 5, LINE OUT TO PHONES .
Step 3.	A double beep will indicate that you have accessed the programming mode.
Step 4.	You can now Touch Tone program the features listed in section B below.
Step 5.	When finished programming, hang up and move DIP switch 2 to the OFF position.

3. Accessing the Programming Mode Remotely

Step 1.	Call into the C-2000A from a Touch Tone phone. Note: Call in from another line to avoid C.O. busy signals, etc.
Step 2.	Answer the call from any house phone (device) connected to terminals 4 & 5, LINE OUT TO PHONES.
Step 3.	From either phone enter *# followed by the six digit security code (factory set to 845464 , see Programming section C).
Step 4.	A double beep will indicate that you have accessed the programming mode.
Step 5.	You can now Touch Tone program the features listed in section B below.

Note: Programming from a cell-phone may not be suitable in areas with weak coverage.

B. Quick Programming Features

	Enter Digits	- then -	Memory Location
Privacy Number (factory disabled)	0-6 digits (0-9)	+	#00
Entry phone 1 keyless entry codes (factory disabled)	4-6 digits (0-9)	+	#11 - #16
* Entry phone 1 one time use keyless entry codes (factory disabled)	4-6 digits (0-9)	+	*#11 - *#16
Entry phone 2 keyless entry codes (factory disabled)	4-6 digits (0-9)	+	#21 - #26
* Entry phone 2 one time use keyless entry codes (factory disabled)	4-6 digits (0-9)	+	*#21 - *#26
Entry phone 3 keyless entry codes (factory disabled)	4-6 digits (0-9)	+	#31 - #36
* Entry phone 3 one time use keyless entry codes (factory disabled)	4-6 digits (0-9)	+	*#31 - *#36
Entry phone 4 keyless entry codes (factory disabled)	4-6 digits (0-9)	+	#41 - #46
* Entry phone 4 one time use keyless entry codes (factory disabled)	4-6 digits (0-9)	+	*#41 - *#46
Master keyless entry codes (factory disabled)	4-6 digits (0-9)	+	#51 - #56
* Master one time use keyless entry codes (factory disabled)	4-6 digits (0-9)	+	*#51 - *#56
Doorstrike 1 activation time (.5 - 99 secs, factory set to 00 = .5 secs)	2 digits (00-99)	+	#19
Doorstrike 2 activation time (.5 - 99 secs, factory set to 00 = .5 secs)	2 digits (00-99)	+	#29
Doorstrike 3 activation time (.5 - 99 secs, factory set to 00 = .5 secs)	2 digits (00-99)	+	#39
Doorstrike 4 activation time (.5 - 99 secs, factory set to 00 = .5 secs)	2 digits (00-99)	+	#49
** Auxiliary Contacts:			
Auxiliary contact timing (.5 - 99 secs, factory set to 00 = .5 secs, DIP switch 1 off)	2 digits (00-99) +	#59
1. Entry phone triggered timed activation (factory setting, DIP switch 1 off)	1 +	#60
2. Entry phone triggered continuous activation	2 +	#60
3. Entry phone triggered ring cadence activation	3 +	#60
4. Auxiliary input triggered timed activation	4 +	#60
Maximum entry phone ring count (1 - 99 rings, factory set to 5 rings)	2 digits (01-99)	+	#61
Enable entry phone ringing (factory setting)	1	+	#62
*** Disable entry phone ringing	0	+	#62
Security code (factory set 845464)	6 digits (0-9)	+	#47
Enable entry phone Caller ID (factory setting)	*1		
Disable entry phone Caller ID	*2		
Entry phone calls give custom double ring cadence (factory setting)	*3		
Entry phone calls give standard ring cadence	*4		
Dial "9" to access an outside line	*5		
Instant outside line access (factory setting, for use with private dial tone)	*6		
Enable doorstrike latching commands (factory setting)	*7		
Disable doorstrike latching commands	*8		
Enable entry phone identifier beeps (factory setting)	*9		
Disable entry phone identifier beeps	*0		
Reset all programming to factory default settings	###		

* **Note:** A keyless entry code can be programmed for **EITHER** an unlimited number of uses or one time use, **NOT** both. There can be a maximum of 6 keyless entry codes and/or one time use keyless entry codes per entrance.

** **Note:** Auxiliary contact programming is only to be used if the **C-2000A** is in the **Auxiliary Contact Mode** (DIP switch 1 OFF), see **DIP Switch Programming** section **D**.


*** **Note:** Only entry phone call waiting Caller ID will function in this mode, standard entry phone Caller ID will not.

C. Security Code

This six digit number can be used to access the programming mode. The security code has been factory set to **845464** (V-I-K-I-N-G). It is recommended that you change the security code to a personal 6 digit number. To change the security code, access programming (see **Programming** section **A**). Enter six digits 0-9 followed by **#47**. If you have forgotten your security code, follow the steps in **Programming** section **A, 2. Accessing the Programming Mode Locally (Security Code Bypass Mode)**. **Note:** The security code must be six digits in length and can NOT contain a * or #.

D. Dip Switch Programming

Switch	Position	Description
1	OFF	Auxiliary Contact Mode
1	ON	Doorbell Mode (factory setting)
2	OFF	Normal Operation Mode (factory setting)
2	ON	Security Code Bypass Mode
3	OFF	* Entry Phone automatic disconnect (CPC) disabled
3	ON	Entry Phone automatic disconnect (CPC) enabled (factory setting)
4	OFF	Entry Phone busy signal disabled
4	ON	Entry Phone busy signal enabled (factory setting)



* **Note:** Viking handsfree entry phones require CPC for faster automatic disconnect.

E. Privacy Number

The "Privacy Number" is factory disabled so an entry phone off-hook will automatically ring the house phones. If a "Privacy Number" is programmed, the visitor must Touch Tone dial the number to be able to call into the house. The "Privacy Number" may be from 1 to 6 digits and is stored in location "#00". To disable the "Privacy Number," clear the number's memory location by entering "#00" without any previous digits.

F. Keyless Entry Codes and One Time Use Keyless Entry Codes

Each entry phone may have a combination of up to 6 keyless entry codes or one time use keyless entry codes for Touch Tone keyless entry. The keyless entry codes may be from 4 to 6 digits in length and are stored in locations #11 - #16 for entry phone 1, #21 - #26 for entry phone 2, #31 - #36 for entry phone 3, and #41 - #46 for entry phone 4. Up to 6 master keyless entry codes may be from 4 to 6 digits in length and are stored in locations #51 - #56. The master keyless entry codes can be used at any entry phone. To change any of the keyless entry codes to one time use, insert a * in front of the specific memory location during programming (ie: "*#11"). To clear any keyless entry codes, simply enter the location number (ie: "#11" or "*#11") without any previous digits.

G. Door Strike Activation Time

A single pole double throw relay is available for each entry phone (a second set of contacts are available on solder pads only), and each may be programmed with its own "doorstrike" activation time (programmed in seconds). Each time must be 2 digits (Example: 00 = 1/2 sec.) and is stored in locations #19, #29, #39 and #49 for relays 1 through 4 respectively. All activation times are factory set to 00 (1/2 sec.) **Note:** A buzz sound will be heard in the house phone and entry phone, indicating the door strike relay has been activated and visitors can now open the door.

H. Caller ID

The C-2000A is factory set to send "Caller ID" and "Call Waiting Caller ID" information from the entry phones. If "Caller ID" is not required, enter "*2" while in programming to disable the C-2000A from sending "Caller ID" and "Call Waiting Caller ID" data to the house phones. Enter "*1" to enable "Caller ID" and "Call Waiting Caller ID" data (see **Operation** section A).

I. Entry Phone Ring Cadence

Entry phone calls are factory set to ring the house phones in a custom double ring cadence (.7 seconds on/.3 seconds off/.7 seconds on then 4 seconds off between rings), "*3". The C-2000A can be programmed to give a standard ring cadence for entry phone calls (2 seconds of ring, and 4 seconds off between rings), enter "*4" when in programming. Entry phone ringing can also be disabled by entering "0#62". This is useful when connecting the C-2000A to the SLP-1 to provide unique front and back door chimes.

J. Outside Line Access

1. **Dial "9" to Access the Outside Line** - To program the C-2000A for C.O. dial tone, enter "*5" while programming. To gain access to C.O. dial tone, dial a Touch Tone "9".
2. **Instant Outside Line Access (factory default)** - To program the C-2000A for private dial tone, enter "*6" while programming. House phones will instantly have the outside line dial tone on an off-hook.

K. Maximum Entry Phone Ring Count

The number of times an entry phone call will ring the house phones can be limited in programming. The programmable maximum ring count must be 2 digits and is stored in location "#61". The maximum ring count is programmable from 1 - 99 and factory set to (05) 5 rings.

L. Doorbell Switch Input and Auxiliary Contact Output

1. Doorbell Mode (DIP Switch 1 ON - factory setting)

With the **C-2000A** in the doorbell mode (DIP switch **1 ON**), a normally open switch (SPST 6-16V lighted or non-lighted doorbell button, etc.) can be connected to terminals 26 and 27 (**DOORBELL SWITCH / AUX INPUT**). This switch should be located near entry phone 1. Door chime power (normally connected to a doorbell button) can be routed through terminals 28 and 29 (**N.O. AUX CONTACT OUTPUT**). A momentary closure on the **C-2000A DOORBELL SWITCH** input terminals will momentarily activate the **AUX CONTACT OUTPUT** terminals for the same duration, activating your door chime. Entry phone 1 will be called, automatically answer (see the Technical Practice for your entry phone) and begin ringing the house phones (terminals 4 and 5 **LINE OUT TO PHONES**). The house phones can then be answered, doorstrike commands entered, etc. (see **Operation** sections **A-E**). **Notes:** *Entry phone 1 ringing the house phones can be disabled in this doorbell mode, if it is desirable to have the doorbell chime but not the house phones ring. This option can only be used if there is only one entry phone on the C-2000A. Program the C-2000A with "0#62" (disable entry phone ringing). When the doorbell chimes, picking up a house phone will instantly connect the house phone to the entry phone. If the user presses the doorbell switch again while their call is either ringing the house phones or while talking to the house, the auxiliary relay will activate each time they press the doorbell switch (causing the doorbell to chime again).*

2. Auxiliary Contact Mode (DIP Switch 1 OFF)

With the **C-2000A** in the auxiliary contact mode (DIP switch **1 OFF**), the auxiliary contact output can be programmed (see **Programming** section **B**) to activate in 3 different patterns when entry phones 1-4 are off-hook. These patterns include a momentary activation, a continuous activation while the entry phone is in use, and a ring cadence pattern. A fourth programmed setting is also available for a timed activation of the auxiliary relay from a contact closure.

a. Entry Phone Triggered Timed Activation (0.5 second factory default with DIP switch 1 OFF)


With the entry phone triggered timed activation programmed (**1** followed by **#60**), when any entry phone is activated, the auxiliary contacts will activate for the programmed time (0.5 - 99 seconds) in memory location **#59** (see section **M** below).

b. Entry Phone Triggered Continuous Activation

With the entry phone triggered continuous activation programmed (**2** followed by **#60**), when any entry phone is activated, the auxiliary contacts will activate continuously (latch) until the entry phone disconnects. This is ideal for controlling video cameras, lights, etc. In this mode only, when a house phone has dialed a monitor command (**#1**, **#2**, **#3** or **#4**) to connect to an entry phone, the **C-2000A** will latch the auxiliary relay during the "monitor" once the entry phone answers (so a camera or light can be activated while monitoring).

c. Entry Phone Triggered Ring Cadence Activation

With the entry phone triggered ring cadence activation programmed (**3** followed by **#60**), when entry phone 1 is activated, a repeating 1 second on and 3 seconds off auxiliary contact pattern is generated. When entry phone 2, 3, or 4 is activated, a repeating double burst contact pattern is generated with 3 seconds off between patterns. The auxiliary contact pattern stops when the house phone answers the call from the entry phone. This is ideal for controlling visual ring indicators, or connecting to a model **SLP-1** for unique front and back door chimes.



d. Auxiliary Input Triggered Timed Activation

With the auxiliary input triggered timed activation programmed (**4** followed by **#60**), a momentary contact closure on the **DOORBELL/AUX INPUT** will activate the auxiliary contacts for the programmed time (0.5 - 99 seconds in memory location **#59**, see section **M** below). The auxiliary contacts may be used to provide an additional relay or may be used to add doorstrike entry to an entry phone that does not have a Touch Tone keypad. The auxiliary input contacts may also be used for timed operation of other devices such as yard lights, etc. and can be triggered by the second set of door entry contacts (available through solder pads on the **C-2000A PCB**).

M. Auxiliary Contact Timing

To program the length of time the "**AUXILIARY CONTACT**" is activated when triggered from an entry phone or the "**AUX INPUT**", enter **00 - 99** followed by **#59**.

Operation

A. Visitors

When a visitor presses the call button (comes off-hook) on the entry phone, the **C-2000A** will begin ringing the house phones and "Caller ID" information is sent. If a house phone is on a C.O. call, call waiting tones and "Call Waiting Caller ID" information is sent. A Touch Tone "**#**" from the house phone will put the C.O. call on hold and connect the house phone to the entry phone (beeps will be heard, indicating which entry phone you are connected to). Enter Touch Tones "******" to momentarily activate that entry phone doorstrike and return to the C.O. call or enter "**#**" to just return to the C.O. call without activating the doorstrike. If the doorstrike is activated, a buzz sound will be heard confirming the strike has been activated.

If you require the door strike to remain on continuously (ie: a truck delivery), enter Touch Tones "***1**" to continuously activate that relay and return to the C.O. call. A 5 second buzz sound will indicate the door strike relay is latched on. When the visitor calls in again (ie: they are finished unloading the truck), enter Touch Tones "***0**" to deactivate the relay. Alternatively, the doorstrike relay can be de-activated by going off-hook with any house phone and entering **#1*0** for doorstrike relay 1, **#2*0** for doorstrike relay 2, etc. See **Operation** section **C**. A short buzz will indicate the door strike relay is off.

Entry Phone	Caller ID and Call Waiting ID
1	"Entry Phone 1"
2	"Entry Phone 2"
3	"Entry Phone 3"
4	"Entry Phone 4"

B. Monitoring

Tenants may dial out to an entry phone that supports auto-answering capability by dialing “#1”, “#2”, “#3” or “#4” to call entry phones 1-4 respectively. All Viking Handsfree Entry Phones are equipped with an Auto-Answer feature.

C. Activating Doorstrike/Gate

You may activate the doorstrike relay without calling out to the entry phone. Refer to the chart at the right for dialing strings. When you momentarily activate a doorstrike relay, it will activate for the amount of time specified in **Programming**, section F.

* **Note:** The latch command can be disabled (see **Programming** section B).

Entry Relay	Momentarily Activate Doorstrike	* Latch Doorstrike	Un-Latch Doorstrike	Toggle Doorstrike Relay
1	#1**	#1*1	#1*0	#1*#
2	#2**	#2*1	#2*0	#2*#
3	#3**	#3*1	#3*0	#3*#
4	#4**	#4*1	#4*0	#4*#

D. Privacy Number

The privacy number feature is useful for preventing unwanted (prank) entry phone calls from visitors. If a privacy number has been programmed, an off hook entry phone is given 4 seconds of dial tone to allow the visitor to enter the privacy number. If the visitor enters the correct privacy number, the **C-2000A** will ring the house phones. If they enter an incorrect number, they will be disconnected. If a privacy number is not programmed, then an off-hook entry phone will immediately ring the house phones. **Note:** The “Privacy Number” may be programmed with the first 6 digits of the actual home/office phone number. Visitors may dial the actual 7-digit phone number as if they are making an actual telephone call to the home/office.

E. Keyless Entry Codes and One Time Use Keyless Entry Codes

Touch Tone keyless entry codes may be used by the tenants to provide keyless entry. Each entry phone may have up to 6 keyless entry codes. There are also up to 6 master keyless entry codes which can be used at all four entry locations. If a keyless entry code has been programmed, an off-hook entry phone is given 4 seconds of dial tone before ringing the house phone. During this time a Touch Tone “#” + the “**keyless entry code**” may be entered.

A correct keyless entry code will provide a timed doorstrike activation for that entry phone location. One time use keyless entry codes function as described above but can only be used **ONCE**. After the one time use keyless entry code has been used, it is instantly cleared from the **C-2000A**’s memory. This is ideal for issuing keyless entry codes to service personnel, etc. **Note:** A short buzz sound indicates when the relay has been activated and the visitor can now open the door.

F. Operation Commands

	Touch Tone Commands
Activate doorstrike relay	* *
Continuously activate (latch) doorstrike relay	* 1
Continuously de-activate (unlatch) doorstrike relay	* 0
Toggle relay from last position	* #
Answer or disconnect an entry phone call	#
Monitor entry phone 1	# 1
Monitor entry phone 2	# 2
Monitor entry phone 3	# 3
Monitor entry phone 4	# 4

G. Compatible Viking Equipment

The **C-2000A** is compatible with the Viking entry phones shown below, as well as any standard analog phone. If auto-answer is required for monitoring, use Viking models **E-10**, **E-20A**, **E-30**, **E-40** or **K-1700-3** as entry phones. If Touch Tone keyless entry is required, use Viking models **K-1700-3** or **K-1900-8**.



Product Support Line...715.386.8666

Fax Back Line...715.386.4345

Due to the dynamic nature of the product design, the information contained in this document is subject to change without notice. Viking Electronics, and its affiliates and/or subsidiaries assume no responsibility for errors and omissions contained in this information. Revisions of this document or new editions of it may be issued to incorporate such changes.